

## www.hammondmfg.com

156C

## D.C. Reactors or Filter Chokes Low to Medium Current

## Features

- Economical "open bracket" channel mount.
- Tolerance of 15% on both inductance & resistance.
- Inductances measured at rated D.C. current.
- Minimum 5" long leads.
- Units will exhibit less inductance at slightly higher currents or more inductance at lower currents.
- Perfect for high voltage power supply filtering.
- Every unit is Hipot tested (100%) at 1,500 VAC
- Units are vacuum impregnated with polyurethane varnish for quiet and long life operation.

Mechanical	
А	2.81" / 71.4 mm
В	1.5" / 38.1 mm
С	1.69" / 42.9 mm
D	2.38" / 60.5 mm
G	0.19" / 4.8 mm
Weight	0.5 lbs / 0.23 kg
Electrical	
Inductance (+/- 15%)	1 <i>5</i> 0H
D.C. Current	8 ma.
Resistance (+/- 15%)	3700 ohms
Maximum Operating Volt (D.C.)	400V

